
# UM4730/UM8000 Quick Reference Card





### Welcome!

Your organization's new UNIVERGE® UM4730/UM8000 unified messaging system is designed to provide you with the same convenient access to your messages whether you are at your desk or calling in over the telephone. When you call in, our interface saves you time and effort when sending, retrieving, and managing messages.

‡Please be sure that this is the most recent version of the document by checking "http://www.partnerexpress.com".

### **Before You Start**

To set up UM4730/UM8000, your system administrator will give you the following information.

UM4730/UM8000 internal number:

\_\_\_\_\_

UM4730/UM8000 external number:

\_\_\_\_\_

Your subscriber ID:

\_\_\_\_\_

Your system administrator may also give you a default security code to use when you log on to UM4730/UM8000 for the first time.

### **Gaining Access to Your Mailbox**

Follow these simple steps to start using UM4730/UM8000.

- 1. Call the UM4730/UM8000 internal or external number.
- 2. Enter your subscriber mailbox number.
- 4. Enter a security code (or the default code, if your administrator has given you one).

## **Performing Common Tasks**

If you're looking for a quick hint on how to perform a specific task, read on.

### **Message Playback Options**

If you want to	Then enter
Slower	4
Softer/Louder	5
Faster	6
Backward	7
Pause	8
Forward	9
Exit	*

#### Main

If you want to	Then enter
Check for new messages	4
Leave a message	5
Review messages	6
Change setup	7
Change call transfer and message delivery status	76
Change security code and mailbox names	77
Switch personal greetings	7 4 5

### **Quick Message Shortcuts**

If you want to	Then enter
Repeat the message	3 #
Save message as new (new messages only)	30
Check the next message	3 5
Delete the message	3 6
Archive the message	3 7
Hear when the message was sent	38
Redirect the message	3 9
Exit quickly	*

### **Use These Keys Anytime**

If you want to	Then enter
Respond "yes."	1
Respond "No."	2
Return to the Main Menu	*
Go back one level	#